



SDC's WRC Series 2-Channel wireless transmitter/receiver solution is specifically designed to be used as a receptionist button or remote release for single or dual door access control applications.

433MHZ 2-BUTTON PENDANT TRANSMITTER

LIST



- Operates with 400WRC-R2
- Frequency: 433.92MHz
- Housing: Keychain type
- Voltage: 6VDC

- Battery Replacement: – CR2016 Button Cell 3V Lithium battery (x 2)
- Transmitting distance: 160 feet (no obstructions)
- Activation: Hold “A” or “B” button for 1 sec.

Model	Description	
WRC-2B	433MHz 2-Button Pendant Wireless Transmitter	50.00



433MHZ 2-CHANNEL RECEIVER

LIST



- Size with housing (approx.): 2.5" H x 1.75" W x 1.2" D
- Frequency: 433.92MHz
- Environmental: Indoor
- Operating Temperature: -22°F – 140°F
- Input Voltage: 24VDC
- Current consumption: 9mA @24VDC (standby); 46mA (max)

- Relay Outputs: Two (2) Dry, Form C (SPDT)
- Contact rating: 10A@30VDC (resistive)
- Wiring connections: 12", 8-wire pigtail
- Transmitter coding capacity: 30 (fixed code)
- Transmitter programming using onboard learning button and status LED

Model	Description	
WRC-R2	433MHz 2-Channel Wireless Receiver	81.00



Mini Consoles

Distributor Discount Code

WK LIST

Mini Consoles provide control for one or two doors. Momentary or maintained push button switches with Bi-Color LED indicators.

**Dimensions:** 4-1/8" W x 3-1/8" H x 6-1/4" L  
**Contacts:** 5 Amp @ 30VDC

**Color:** Beige  
**Power:** 24VDC @ 0.02 Amp required for each LED



DTMO-1	One momentary switch and one LED	250.00
DTMO-2	Two momentary switches and two LEDs	275.00
DTMOMA-2	One momentary, one maintained switch and two LEDs	350.00
DTMA-2	Two maintained switches and two LEDs	275.00

