

101 Series Annunciators



101-1A



101-1AK



101-4AM



101-PAM

Compatible with all ExitCheck® systems, the 101 Series Annunciators provide door status at a remote location such as a nurse's station, guard station or office. The tri-color LED provides precise delay mode status.



SPECIFICATIONS

Faceplate 20 Gauge Stainless Steel

Voltage 20 mA @ 12/24VDC

LED Tri-Color Green (Secure),
Amber (Alarm/Door Locked),
Red (Alarm/Door Unlocked)

Weight 1.5 lbs



MODELS

101-1A Single Door Annunciator

101-4AM Four Door Annunciator

101-1AK Single Door Annunciator with Key Control

101-PAM Single Door Annunciator with Push Switch

101-SP External 15 Watt Speaker

101-SPSN Remote Annunciator with Speaker & Siren



 **HOW TO ORDER**

1| SPECIFY MODEL

Model	1 Gang	2 Gang	Tri-Color LED	Audible Alarm	Description
101-1A	X		X	X	Remote or local single door annunciator
101-4AM		X	4 LEDs	X	Remote four door annunciator with audible alarm mute button
101-1AK		X	X	X	Remote or local single door annunciator with 2 function key switch for on/off and reset. Accepts standard 1-1/8" to 1-1/4" Mortise key cylinder (Mortise key cylinder not included).
101-PAM		X	X	X	Remote single door annunciator with 3 push button switches for momentary access. On/off and audible mute button (Recommended for remote installation only).
101-SP	External 15 watt speaker connects directly to 1511S or 1511T for enhanced decibels onsite or remote voice message announcement. Speaker driver may be provided by others for extreme decibel requirements.				
101-SPSN	X				Remote annunciator with speaker and 80db tone. Duplicates ExitCheck 101-DE/KDE alternating voice message and tone.



101-1A



101-4AM



101-PAM



101-1AK



101-SPSN



101-SP

CYLINDER OPTION

CYL-6KDQ 6 pin, 1-1/8" Mortise Cylinder, Keyed different, 626 Dull Chrome

CYL-6KAQ 6 pin, 1-1/8" Mortise Cylinder, Keyed alike, 626 Dull Chrome

